

Programmable Power Guard Phidget



When high-power motor stalls or stops suddenly, it can generate a high-voltage surge that can damage the circuitry of the motor controller and burn out the power supply. This Power Guard Phidget is designed to protect your hardware from such an event by preventing current from flowing back into the power supply, and by providing a heatsink and fan for the excess power to dissipate. This board is designed for high current systems and is capable of protecting your equipment from even the largest of power spikes. Simply connect your power supply's positive wire to the 8-30V input lug, connect your device's positive wire to the output lug, and wire both grounds to the ground lug. The SAF1000 connects to a port on a **VINT Hub**. See the "Compatible Products" tab for a list of hubs.

Power Control and Safety Features

Since this is an intelligent VINT device, the over voltage trigger can be modified in software to accommodate for different power supplies. Similarly, the fan can be switched on or off, or it can be set to turn on when a certain temperature threshold is passed. You can also choose to switch the power off through software, like a relay. Even if communication between this board and the computer is interrupted, it will continue to power the device and protect against the last chosen overvoltage trigger.

Isolated for Stability

The VINT port on this board is electrically isolated from the rest of the board in order to improve stability by eliminating ground loops.

We strongly recommend using this Phidget according to the table below:

Recommended Use

Controller	Motor Rated Current	Suggested Power Guard
-------------------	----------------------------	------------------------------

STC1000	Less than 1.5A	None
STC1000	1.5A to 5A	SAF2000
STC1000	Greater than 5A	SAF1000

DCC1000	Less than 1A	None
DCC1000	1A to 5A	SAF2000
DCC1000	Greater than 5A	SAF1000

Product Specifications

Board Properties

Controlled By VINT

Power Supply Protector

Overvoltage Setting	Selectable via software 8 – 33 VDC
Overtemperature Trigger	125 °C
Sampling Interval Min	100 ms/sample
Sampling Interval Max	60 s/sample
Fan Trigger	75 °C

Electrical Properties

Continuous Current	50 A
Current Consumption Min (VINT Port)	100 μ A
Supply Voltage Min	8 V DC
Supply Voltage Max	30 V DC
Power Consumption	250 mW

Physical Properties

Recommended Wire Size	6 – 14 AWG
Operating Temperature Min	-40 °C
Operating Temperature Max	85 °C