

Power Supply 24VDC 15A



The PSU4016 provides efficient power at 24VDC, 15.0 Amp, 350 Watts. It is protected against over-current, over-voltage, and over-temperature. The output voltage can be adjusted between 21.6 and 28.8V using the adjustment screw.

This power supply protects itself from over-current situations by momentarily cutting power to the output. If your application requires a power supply that will handle these over-current situations more gracefully, you should look at the [PSU4017_0 Current Limiting Power Supply](#).

This power supply requires you to supply your own power cable to provide power from the mains. You will need to cut and strip the end of the cable to connect it to the power supply. We recommend crimping the connectors included with this power supply to the end of the power cable for a better electrical connection to the terminals, as pictured above.

Mains Voltage Setting



Caution: Before using this power supply, ensure that you flip the red switch on the side of the supply so it displays the voltage that matches your country's mains voltage.

Comes packaged with



- 6 large crimp connectors
- 4 small crimp connectors

Product Specifications

Electrical Properties

Output Voltage	24 V
Power Supply Voltage Min	21.6 V DC
Power Supply Voltage Max	28.8 V DC
Power Supply Current	15 A
Output Power	350 W
AC Input Voltage Min	* 90 V AC
AC Input Voltage Max	* 132 V AC
AC Input Frequency Min	50 Hz
AC Input Frequency Max	60 Hz
Protection Circuitry	Over-Current, Over-Voltage, Over-Temperature

Physical Properties

Operating Temperature Min	-25 °C
Operating Temperature Max	70 °C

*This is in low range. There is a dip switch on board that will set the supply into high range which changes the input range to 180-264VAC.