

PhidgetAnalog 4-Output



Note: The 1002_0B is identical to the 1002_0, except that you have the option of whether you want to include the USB cable.

The PhidgetAnalog 4-Output Produces a voltage over -10V to +10V at a maximum of $\pm 20\text{mA}$. If this current is exceeded an error will be thrown to notify that the voltage may have dropped below the setpoint. The voltage is produced with 12 bit resolution (4.8mV).

The board is not isolated and all 4 channels share a common ground.

All the power is supplied by via USB.

* The maximum output frequency is dependent on the speed of your system.

Comes Packaged with

- A Hardware mounting kit (4 nuts and bolts (M3), 4 plastic spacers)

Product Specifications

Board Properties

Controlled By	USB (Mini-USB)
API Object Name	VoltageOutput
USB Voltage Min	4.6 V DC
USB Voltage Max	5.5 V DC
Current Consumption Min	55 mA
Current Consumption Max	300 mA
Available External Current	(per channel) 20 mA
Recommended Wire Size	16 – 26 AWG
USB Speed	Full Speed
Operating Temperature Min	0 B°C
Operating Temperature Max	70 B°C

Voltage Outputs

Number of Voltage Outputs	4
Output Impedance (Channel Enabled)	500 m0©
Output Impedance (Channel Disabled)	4 k0©
Voltage Output Max	B± 10 V DC
Output Voltage Resolution	(12 bit) 4.8 mV DC
Capacitive Load Stability	4 nF
Frequency Max	Variable*

* The maximum output frequency is dependent on the speed of your system.