12V/0.8Kg-cm/46RPM 50:1 DC Gear Motor



Product Description

The 3256 is a 12 volt gear motor, generating 0.82 Kg-cm of torque at 46 RPM. It is very efficient for its size, so less power is lost in the form of heat.

This family of motors (3254, 3255, 3256, 3257) have the same gearbox type and mounting metrics as the (3258, 3259, 3260) family of motors.

Motor Controller and Connection

The 3256 DC motor connects to either of the following controllers:

- 1064 PhidgetMotorControl HC
- 1065 PhidgetMotorControl 1-Motor

You'll need to solder wires to the contacts of the motor in order to connect it to a controller.

Related Products

- 3256E 12V/0.8Kg-cm/46RPM 50:1 DC Gear Motor w/ Encoder
- 3254 12V/0.2Kg-cm/230RPM 10:1 DC Gear Motor
- 3255 12V/0.3Kg-cm/127RPM 18:1 DC Gear Motor
- 3257 12V/1.6Kg-cm/23RPM 100:1 DC Gear Motor

Resources

- DC Motor and Controller Primer
- Mechanical Drawing

Product Specifications

Motor Properties

Motor Type	DC Motor
Output Power (Mechanical)	590 mW
Maximum Speed at Rated Voltage	46 RPM
Rated Torque	820 g·cm
Stall Torque	5.1 kg·cm

Electrical Properties

Rated Voltage	12 V DC
Rated Current	90 mA
Stall Current	260 mA

Physical Properties

Shaft Diameter	6 mm	
Weight	137 g	
Recommended Wire Size (Motor)	20 -26 AWG	

Gearbox Specifications

Gearbox Type	Spur	
Gear Ratio	50 : 1	
Number of Gear Trains	4	
Maximum Strength of Gears	12 kg⋅cm	
Shaft Maximum Axial Load	35 N	
Shaft Maximum Radial Load	25 N	