12V/6.6Kg-cm/49RPM 51:1 DC Gear Motor



Product Description

The 3267 is a 12 volt gear motor, generating 6.63 Kg-cm of torque at 49 RPM. Since this motor has a lower power output for its size, you can expect it to have a longer lifespan than other motors.

The planetary gearbox on this motor is more sophisticated than a typical spur gearbox and will provide greater efficiency, higher torque, and quieter motor operation.

Motor Controller and Connection

The 3267 DC motor connects to either of the following controllers:

- 1064 PhidgetMotorControl HC
- 1065 PhidgetMotorControl 1-Motor

Related Products

- 3267E 12V/6.6Kg-cm/49RPM 51:1 DC Gear Motor w/ Encoder
- 3265 12V/0.5Kg-cm/670RPM 3.7:1 DC Gear Motor
- 3266 12V/1.9Kg-cm/175RPM 14:1 DC Gear Motor
- 3268 12V/17.3Kg-cm/18RPM 139:1 DC Gear Motor

Resources

- DC Motor and Controller Primer
- Mechanical Drawing

Product Specifications

Motor Properties

Motor Type	DC Motor
Output Power (Mechanical)	3.8 W
Maximum Speed at Rated Voltage	49 RPM
Rated Torque	6.6 kg·cm
Stall Torque	46.8 kg·cm

Electrical Properties

Rated Voltage	12 V DC
Rated Current	650 mA
Stall Current	2.4 A

Physical Properties

Shaft Diameter	8 mm
Weight	526 g

Gearbox Specifications

Gearbox Type	Planetary
Gear Ratio	50 ⁸⁰¹ ? ₈₉₅ : 1
Number of Gear Trains	3
Maximum Strength of Gears	61 kg·cm
Shaft Maximum Axial Load	50 N
Shaft Maximum Radial Load	35 N